

Overview

HPE Nimble Storage Adaptive Flash Arrays

Like having two flash arrays in one

The HPE Nimble Storage Adaptive Flash array is truly adaptive. It is designed for both Primary and Secondary flash workloads. It is a Hybrid Flash array for mixed, primary workloads, where cost-efficient flash performance is important. It is a Secondary Flash array for backup and DR while allowing you to put your backup data to work.

Experience the Power of Predictive

HPE Nimble Storage Adaptive Flash Arrays combine a flash-efficient architecture with HPE InfoSight predictive analytics to achieve fast, reliable access to data and 99.9999% guaranteed availability¹. Your storage investment made today will support you well into the future, thanks to our technology and business-model innovations.

What's new

Now HPE Nimble Storage Adaptive Flash Arrays are NEBS (Network Equipment Building System) certified.

The HPE Nimble Storage family of adaptive flash arrays deliver the functionality of two cost-effective flash arrays in one – Hybrid flash and Secondary flash. The new arrays are up to 65% faster than and more than twice as scalable as previous adaptive flash arrays. The arrays use inline variable block deduplication and compression for maximum data reduction. Adaptive arrays are designed to deliver business value today and tomorrow as demonstrated by our **timeless storage**.

NOTE: For more information about the entire HPE Nimble Storage product portfolio, go to <https://www.hpe.com/us/en/storage/nimble.html>.



HPE Nimble Storage Adaptive Flash Array³

(Base array, 4U; 21 bays hold carriers with Large Form Factor HDDs, 3 bays hold Dual Flash Carriers with Small Form Factor SSDs)

Standard Features

HPE InfoSight predictive analytics

- Automatically predicts and resolves 86% of problems before you even know there is an issue.
 - Transforms the support experience through predictive automation and Level 3-only support.
 - Sees across the infrastructure stack and resolves problems beyond storage.
 - Simplifies planning with prescriptive forecasts into capacity, performance, and bandwidth needs.
 - Makes infrastructure smarter and more reliable by learning from the installed base.
-

Radical Simplicity

- Simple to deploy. Simple to use. Simple to manage.
 - Cloud-ready. Deploy flash on-premises or in the cloud with common data services and mobility between all-flash, hybrid flash, and HPE Cloud Volumes.
 - Timeless Storage means no worries today or tomorrow. Flash arrays come with a satisfaction guarantee, all-inclusive software licensing, flat support pricing, no forklift upgrades, and an option to receive a free faster controller upgrade after three years.
 - Radically easy to integrate with many ecosystems. Deep integration with VMware, MS applications, Oracle, Veeam, and others.
 - No data worries. 99.9999% (six-nines) guaranteed availability¹. Triple+ Parity RAID tolerates 3 simultaneous drive failures plus additional protection through intra-drive parity.
-

Flash Performance for Mixed, Mainstream Workloads

- Speed and efficiency for mixed workloads with sub-millisecond response and greater efficiency than other hybrid arrays³.
- Write to cost-optimized disk at flash speeds through write serialization – defying the physics of mechanical spindles.
- Assign and change the service level of any volume at the click of a button ("Auto Flash", "All Flash", or "Minimal Flash").
- Always-on data reduction delivers up to 5X or more space savings without performance penalty⁴.

Put Your Backup Data to Work

- Secondary storage that does real work: Flash performance lets you use your backup data for development/test, QA, analytics, and more.
 - Eliminates the need for full backups: And speeds synthetic full backups from hours to minutes. Native application-consistent snapshots and replication plus integration with leading backup software.
 - Restore backup data instantly. Fast backup verification - test backups more often. Eliminate the need to restore by running workloads directly.
 - Deep integration with Veeam availability software. Array capabilities accessible through the Veeam GUI.
 - Backup and DR at a third of the cost, when replicating from all-flash to adaptive flash.
 - Very cost-effective with powerful dedupe and compression. App-granular, FIPS-certified encryption provides data at-rest and over-the-wire protection. Secure data shredding is built-in.
 - Redundant, hot-swap components including controllers, power supplies, SSDs, HDDs, and IO cards.
-

NEBS Level 3 Certified

- HPE Nimble Storage Adaptive Flash Arrays are NEBS (Network Equipment Building System) level 3 certified
 - Ideal for network equipment providers and communication service providers requiring NEBS certified Hybrid Flash storage arrays for their telecom infrastructure
 - NEBS Level 3 certified for all Nimble Storage Adaptive Flash Arrays (HF20, HF20C, HF20H, HF40, HF40C, HF60, and HF60C)
-

Standard Features

| HPE Nimble Storage Adaptive Flash Array models | | | | | | | | |
|---|---------------|---------------|-----------------|----------------------|----------------------|----------------------|----------------------|--------------------------------|
| HPE Nimble Storage HF-Series array ^{1,2} | HF20 | HF20H | HF20C | HF40 | HF40C | HF60 | HF60C | Scale-out ³ 4X HF60 |
| Raw capacity (TB/TiB)⁴ | 21-210/19-191 | 11-211/10-192 | 21-1050/19-955 | 21-504/19-458 | 21-1470/19-1337 | 21-1260/19-1146 | 21-1470/19-1337 | 5040/4584 |
| Usable capacity (TB/TiB)⁴ | 16-169/14-153 | 7-164/6-149 | 16-846/14-770 | 16-406/14-369 | 16-1185/14-1078 | 16-1016/14-924 | 16-1185/14-1078 | 4065/3697 |
| Effective capacity⁵ | 81-845/74-768 | 34-821/31-746 | 32-1692/28-1540 | 81-2030/74-1846 | 32-2370/28-2156 | 81-5080/74-4621 | 32-2370/28-2156 | 326-20324/297-18484 |
| Max. # of expansion shelves | 6 | 6 | 6 | 6 | 6 | 6 | 6 | 24 |
| Flash capacity (TB/TiB)⁴ | 1.4-28/1.3-25 | 0.9-28/0.8-25 | 0.7-38/0.6-35 | 1.4-48/1.3-43 | 0.7-60/0.6-54 | 1.4-156/1.3-142 | 1.4-156/1.3-142 | 624/567 |
| RAID level Triple+ Parity | | | | | | | | |
| Onboard iSCSI/Mgmt. 1 Gb/10 Gb ports per array⁶ | 4 | 4 | 4 | 4 | 4 | 4 | 4 | 16 |
| Optional iSCSI 1 Gb ports per array | 4, 8, 12, 16 | 4, 8, 12, 16 | 4, 8, 12, 16 | 4, 8, 12, 16, 20, 24 | 4, 8, 12, 16, 20, 24 | 4, 8, 12, 16, 20, 24 | 4, 8, 12, 16, 20, 24 | 96 |
| Optional iSCSI 10 Gb ports per array | 4, 8, 12, 16 | 4, 8, 12, 16 | 4, 8, 12, 16 | 4, 8, 12, 16, 20, 24 | 4, 8, 12, 16, 20, 24 | 4, 8, 12, 16, 20, 24 | 4, 8, 12, 16, 20, 24 | 96 |
| Optional FC 8 Gb/16 Gb ports per array | 4, 8, 12, 16 | 4, 8, 12, 16 | 4, 8, 12, 16 | 4, 8, 12, 16, 20, 24 | 4, 8, 12, 16, 20, 24 | 4, 8, 12, 16, 20, 24 | 4, 8, 12, 16, 20, 24 | 96 |
| Max. power requirement (watts/kVA) | 750/0.833 | 650/0.722 | 750/0.833 | 850/0.944 | 850/0.944 | 900/1.000 | 900/1.000 | 3600/4.000 |
| Thermal (BTU) | 2460 | 2132 | 2460 | 2788 | 2788 | 2952 | 2952 | 11,808 |

NOTES:

¹ HPE Nimble Storage HF20/HF20C and HF40/HF40C Adaptive Flash array support scale up to any model within the HF family. HF20H Adaptive Flash array supports scale up to the HF40 Adaptive Flash array.

² The HF20H Adaptive Flash array consists of up to 22 HDDs and 2 Dual Flash Carriers (DFCs). All other HF-Series models consist of up to 21 HDD drives and 3 DFCs (holding up to 6 SSDs).

³ Scale-out configuration consists of 4X HF60 Adaptive Flash arrays, each with six maximum capacity expansion shelves.

⁴ Raw, usable, and effective capacities are shown in TB (10¹² bytes) and TiB (2⁴⁰ bytes). Usable and effective capacities take into account space used for parity, spares, SSD cache, and system overhead.

⁵ Deduplication currently supported on HF20H, HF20, HF40, and HF60; the HF20C, HF40C, and HF60C does not support dedupe and is capacity optimized to scale to over 1PB.

⁶ Each array controller has 2 x 10GbaseT ports built in. Optional ports are 1GbaseT, 10GbaseT, 10GbE SFP+, or 8/16Gb FC.

Standard Features

Expansion Shelves for HPE Nimble Storage Adaptive Flash Arrays

ES3 Expansion Shelf for Adaptive

| | |
|--|-----------------------------|
| Raw capacity (TB/TiB) ⁸ | 21–210/18–190 |
| Usable capacity (TB/TiB) ⁸ | 16–169/14–154 ¹⁰ |
| Effective capacity (TB/TiB) ^{8,9} | 32–337/28–308 |
| Flash capacity (TB/TiB) ⁸ | 0.7–108/0.7–98 |
| Max. power requirement (Watts/kVA) | 500/0.56 |
| Thermal (BTU) | 1638 |

NOTES:

⁸ Raw, usable, and effective capacities are shown in TB (10¹² bytes) and TiB (2⁴⁰ bytes). Usable and effective capacities take into account space used for parity, spares, SSD cache, and system overhead.

⁹ Scale-out configuration consists of 4X HF60 Adaptive Flash arrays, each with six maximum capacity expansion shelves.

¹⁰ When attached to a HF20H Adaptive Flash array, capacity is 16–167/14–152.

Host OS Support

Microsoft® Windows® Server, including Microsoft® Hyper-V™ | VMware vSphere™ | HP-UX® | Ubuntu
SUSE® Linux Enterprise | SUSE® Linux Virtualization | Red Hat® Enterprise Linux® | Red Hat® Enterprise Virtualization
CentOS | Oracle® Linux® (UEK and RHEL compatible kernels) | Oracle® Solaris Citrix® | IBM® AIX®

NOTE: For the latest information on supported operating systems refer to Single Point of Connectivity Knowledge (SPOCK) for HPE Storage products, including HPE Nimble Storage. <http://www.hpe.com/storage/spock>

Optional File Controller(s)

Add optimized, secure, and reliable file services to your Nimble Storage Array with one or more pre-configured HPE Storage File Controllers. Augmenting a Nimble Storage Array with a file controller or highly-available file controller cluster creates a unified block/file solution that maximizes your total storage investment. Each HPE Storage File Controller is built on HPE ProLiant DNA and Microsoft Windows Storage Server 2016, and can serve thousands of concurrent users and multiple diverse workloads while providing a straightforward and familiar management experience for IT generalists or storage administrators.

For more information, visit <https://h20195.www2.hpe.com/v2/GetDocument.aspx?docname=a00047729enw>

Service and Support

Warranty

HPE Nimble Storage arrays come with the following warranties:

- 1 year; parts-only warranty for hardware components, including SSDs
- 90 day; software updates for defects

Additionally, HPE Nimble Storage will provide phone support for replacing a defective part. Additional support coverage is required for HPE Nimble Storage Arrays.

NOTE: For hardware warranty claims, defective part must be received before replacement parts are shipped

NOTE: Warranty is provided by HPE Nimble Storage.

NOTE: Link to [HPE Global Limited Warranty and Technical Support](#)

Service and Support

Support is required for all HPE Nimble Storage Arrays. Support SKUs provide up to five years of 24x7 telephone and email support for the arrays and hardware components (Including SSDs reaching the write wear limit) with a choice of Next Business Day (NBD) parts exchange, 4-hour parts delivery, or 4 hour onsite support, access to the HPE InfoSight predictive analytics platform and software updates.

NOTE: Support contract is mandatory for all HPE Nimble Storage products.

Installation Service

HPE Nimble Storage Array Start-up service

On-site installation of a new HPE Nimble Storage Array in a data center with up to six (6) shelves.

HPE Nimble Storage Upgrade service

On-site installation of upgrades kits or expansion shelves for an existing HPE Nimble Storage Array.

NOTE: Installation services are optional for all HPE Nimble Storage products.

Parts and Materials

Hewlett Packard Enterprise will provide HPE-supported replacement parts and materials necessary to maintain the covered hardware product in operating condition, including parts and materials for available and recommended engineering improvements.

Parts and components that have reached their maximum supported lifetime and/or the maximum usage limitations as set forth in the manufacturer's operating manual, product quick-specs, or the technical product data sheet will not be provided, repaired, or replaced as part of these services.

The defective media retention service feature option applies only to Disk or eligible SSD/Flash Drives replaced by Hewlett Packard Enterprise due to malfunction.

Configuration Information

Step 1 - Choose a Base configuration

All HPE Nimble Storage Adaptive Flash Arrays come in a 4U form-factor chassis with (2) controllers with fans and NVDIMM, and (4) 1GbE/10GbE network ports, i.e. (2) per controller for iSCSI or management traffic, and (2) power supplies and

All-inclusive software including HPE InfoSight predictive analytics

Additional host connectivity per controller is indicated in the product descriptions below.

Flash Cache upgrades, network upgrades and expansion shelves are available for integration in the field. Upgrade information will be supplied in the next QuickSpecs update.

HPE Nimble Storage HF-Series Adaptive Flash Arrays – Base Configuration Base Array

SKU Description

| SKU Description | SKU |
|--|--------|
| HPE Nimble Storage HF20C Adaptive Dual Controller 10GBASE-T 2-port Configure-to-order Base Array | Q8H70A |
| HPE Nimble Storage HF20H Adaptive Dual Controller 10GBASE-T 2-port Configure-to-order Base Array | Q8H71A |
| HPE Nimble Storage HF20 Adaptive Dual Controller 10GBASE-T 2-port Configure-to-order Base Array | Q8H72A |
| HPE Nimble Storage HF40 Adaptive Dual Controller 10GBASE-T 2-port Configure-to-order Base Array | Q8H39A |
| HPE Nimble Storage HF40C Adaptive Dual Controller 10GBASE-T 2-port | R0P42A |
| HPE Nimble Storage HF60 Adaptive Dual Controller 10GBASE-T 2-port Configure-to-order Base Array | Q8H40A |
| HPE Nimble Storage HF60C Adaptive Dual Controller 10GBASE-T 2-port | R0P43A |

Step 2 – Choose Head HDD Capacity

All HPE Nimble Storage Adaptive Flash Arrays come with (21) LFF Hard Drives included as standard and supports (3) Dual Flash Carriers with SFF Solid State Drives. The configurations below include three SFF SSDs and accept one optional Flash Upgrade Kit to increase the Flash Cache. Additional capacity can be added by connecting up to (6) expansion shelves to the base array.

NOTE: R2 and non-R2 SKUs are functionally equivalent. The OCA quote tool will guide to the appropriate SKU option when configuring a model. Table below shows Adaptive Flash Array compatibilities with SSD Options.

Configuration Information

Only ONE of the following options can be selected:

| Head HDD Capacity Options | | HF20H | HF20C | HF20 | HF40/ HF40C | HF60/ HF60C |
|---|---|--------|---------|--------|--------------------|---------------------|
| SKU | SKU Description | | | | | |
| Q8B67B | HPE Nimble Storage HF20H Adaptive Array 11TB (11x1TB) FIO HDD Bundle | Yes | No | No | No | No |
| Q8B68B | HPE Nimble Storage HF20/20C Adaptive Array 21TB (21x1TB) FIO HDD Bundle | No | Yes | Yes | No | No |
| Q8B69B | HPE Nimble Storage HF20/20C Adaptive Array 42TB (21x2TB) FIO HDD Bundle | No | Yes | Yes | No | No |
| Q8H75A | HPE Nimble Storage HF20/20C Adaptive Array 84TB (21x4TB) FIO HDD Bundle | No | Yes | Yes | No | No |
| Q8H76A | HPE Nimble Storage HF20/20C Adaptive Array 126TB (21x6TB) FIO HDD Bundle | No | Yes | Yes | No | No |
| Q8H77A | HPE Nimble Storage HF20/20C Adaptive Array 210TB (21x10TB) FIO HDD Bundle | No | Yes | Yes | No | No |
| Q8H44A | HPE Nimble Storage HF40/60 Adaptive Array 21TB (21x1TB) FIO HDD Bundle | No | No | No | Yes | Yes |
| Q8H45A | HPE Nimble Storage HF40/60 Adaptive Array 42TB (21x2TB) FIO HDD Bundle | No | No | No | Yes | Yes |
| Q8B55B | HPE Nimble Storage HF40/60 Adaptive Array 84TB (21x4TB) FIO HDD Bundle | No | No | No | Yes | Yes |
| Q8B56B | HPE Nimble Storage HF40/60 Adaptive Array 126TB (21x6TB) FIO HDD Bundle | No | No | No | Yes | Yes |
| Q8B57B | HPE Nimble Storage HF40/60 Adaptive Array 210TB (21x10TB) FIO HDD Bundle | No | No | No | Yes | Yes |
| Max addressable Capacity (RAW) per platform | | 211 TB | 1050 TB | 210 TB | 504 TB/ 1470 TB | 1260 TB/ 1470 TB |

Step 3 – Choose Head SSD Cache Capacity

| Head HDD Capacity | Minimum Head SSD Cache Required | | | | | | |
|-------------------|---------------------------------|--------|---------|--------|---------|--------|---------|
| | HF20H | HF20C | HF20 | HF40C | HF40 | HF60C | HF60 |
| 11TB | 960GB | N/A | N/A | N/A | N/A | N/A | N/A |
| 21TB | N/A | 720GB | 1440GB | 720GB | 1440GB | 1440GB | 1440GB |
| 22TB | 1920GB | N/A | N/A | N/A | N/A | N/A | N/A |
| 42TB | N/A | 1440GB | 2880GB | 1440GB | 2880GB | 1440GB | 2880GB |
| 84TB | N/A | 2880GB | 5760GB | 2880GB | 5760GB | 2880GB | 5760GB |
| 126TB | N/A | 5760GB | 11520GB | 5760GB | 11520GB | 5760GB | 11520GB |
| 210TB | N/A | 5760GB | 17280GB | 5760GB | 17280GB | 5760GB | 17280GB |

Configuration Information

Head SSD Capacity Options

| For combinations of Bank A and Bank B of the DFC: When both banks are populated, adjacent banks should not differ by more than one step function in SSD capacity e.g. 3x480GB can have 3x240GB or 3x480GB or 3x960GB in the adjacent bank. Not allowed in the adjacent bank would be 3x1920GB or 3x3840GB. | | HF20H | HF20C/ HF40C | HF20 | HF40 | HF60/ HF60C |
|--|--|-------|-----------------|------|------|----------------|
| HF20H: ONE or TWO SSD-packs of the following SSD cache options can be selected. | | | | | | |
| SKU | SKU Description | | | | | |
| Q8B77B | HPE Nimble Storage HF20H Adaptive Array 480GB (2x240GB) FIO Cache Bundle | Yes | No | No | No | No |
| Q8B79B | HPE Nimble Storage HF20H Adaptive Array R2 960GB (2x480GB) FIO Cache Bundle | Yes | No | No | No | No |
| HF20C/HF40C: ONE or TWO SSD-packs of the following SSD cache options can be selected. | | | | | | |
| Q8B80B | HPE Nimble Storage HF20C Adaptive Array 720GB (3x240GB) FIO Cache Bundle | No | Yes | No | No | No |
| Q8B82B | HPE Nimble Storage HF20C Adaptive Array R2 1.44TB (3x480GB) FIO Cache Bundle | No | Yes | No | No | No |
| Q8H80A | HPE Nimble Storage HF20C Adaptive Array R2 2.88TB (3x960GB) FIO Cache Bundle | No | Yes | No | No | No |
| Q8H81A | HPE Nimble Storage HF20C Adaptive Array 5.76TB (3x1.92TB) FIO Cache Bundle | No | Yes | No | No | No |
| Q8H82A | HPE Nimble Storage HF20C Adaptive Array 11.52TB (3x3.84TB) FIO Cache Bundle | No | Yes | No | No | No |
| HF20: ONE SSD-packs of the following SSD cache options can be selected. | | | | | | |
| Q8J28A | HPE Nimble Storage HF20 Adaptive Array 1.44TB (6x240GB) FIO Cache Bundle | No | No | Yes | No | No |
| Q8J29A | HPE Nimble Storage HF20 Adaptive Array R2 2.88TB (6x480GB) FIO Cache Bundle | No | No | Yes | No | No |
| Q8J30A | HPE Nimble Storage HF20 Adaptive Array R2 5.76TB (6x960GB) FIO Cache Bundle | No | No | Yes | No | No |
| R0P02A | HPE Nimble Storage HF20 Adaptive Array 8.64TB (3x1920GB and 3x960GB) FIO Cache Bundle | No | No | Yes | No | No |
| Q8J31A | HPE Nimble Storage HF20 Adaptive Array 11.52TB (6x1.92TB) FIO Cache Bundle | No | No | Yes | No | No |
| R0P03A | HPE Nimble Storage HF20 Adaptive Array 17.28TB (3x3840GB and 3x1920GB) FIO Cache Bundle | No | No | Yes | No | No |
| Q8J32A | HPE Nimble Storage HF20 Adaptive Array 23.04TB (6x3.84TB) FIO Cache Bundle | No | No | Yes | No | No |
| HF40/HF60/HF60C: ONE SSD-packs of the following SSD cache options can be selected. | | | | | | |
| Q8H48A | HPE Nimble Storage HF40/60 Adaptive Array 1.44TB (6x240GB) FIO Cache Bundle | No | No | No | Yes | Yes |
| Q8H49A | HPE Nimble Storage HF60 Adaptive Array 2.88TB (6x480GB) FIO Cache Bundle | No | No | No | | Yes |
| Q8B62B | HPE Nimble Storage HF60 Adaptive Array 5.76TB (6x960GB) FIO Cache Bundle | No | No | No | | Yes |
| Q8H50A | HPE Nimble Storage HF40 Adaptive Array R2 2.88TB (6x480GB) FIO Cache Bundle | No | No | No | Yes | |
| Q8B63B | HPE Nimble Storage HF40 Adaptive Array R2 5.76TB (6x960GB) FIO Cache Bundle | No | No | No | Yes | |
| R0P04A | HPE Nimble Storage HF40/60 Adaptive Array 8.64TB (3x1920GB and 3x960GB) FIO Cache Bundle | No | No | No | Yes | Yes |
| Q8B64B | HPE Nimble Storage HF40/60 Adaptive Array 11.52TB (6x1.92TB) FIO Cache Bundle | No | No | No | Yes | Yes |

Configuration Information

| | | | | | | |
|--------|--|--------------|--------------|-------------|------------------------|------------------------|
| R0P05A | HPE Nimble Storage HF40/60 Adaptive Array 17.28TB (3x3840GB and 3x1920GB) FIO Cache Bundle | No | No | No | Yes | Yes |
| Q8B66B | HPE Nimble Storage HF40/60 Adaptive Array 23.04TB (6x3.84TB) FIO Cache Bundle | No | No | No | Yes | Yes |
| | | HF20H | HF20C | HF20 | HF40/ HF40C | HF60/ HF60C |
| | Platform RAM installed (GB) per controller | 32 | 32 | 32 | 64 | 160 |
| | Min SSD capacity (RAW) range per platform basis (GB) | 960 | 720 | 1440 | 1440/ 720 | 1440 |
| | Max SSD capacity (RAW) range per platform basis (GB) | 15360 | 23040 | 23040 | 23040 | 23040 |
| | Platform Max SSD capacity (RAW)= (Head SSD + ES3 SSD) capacity (TB) | 28TB | 38TB | 28TB | 48TB/ 60TB | 156TB |

Step 4 – Choose Head Networking Option

Only ONE of the following options can be selected. Please refer to configuration guidelines for specific support of networking options on HF-Series arrays.

NOTE: The following minimum ports are recommend for best performance:

- HF20: at least 2-ports
- HF40: at least 4-ports
- HF60: at least 8-ports

NOTE: All 10GbE and 16Gb FC cards include SFP+ optical transceivers

NOTE: Head networking options include a total of two (2x), four (4x), or six (6x) cards which are evenly populated in the two controllers. For example, HPE Nimble Storage 2x10GbE 2-port and 2x16Gb Fibre Channel 4-port FIO Adapter Kit (R0N84A), includes a total of four (4) cards—2x 10GbE 2-port cards and 2x 16Gb Fibre Channel 4-port cards. In this case, each controller (A & B) is populated with one (1) 10GbE 2-port card and one (1) 16Gb FC 4-port card.

| Head Networking Options | | HF20H | HF20C | HF20 | HF40/ HF40C | HF60/ HF60C |
|------------------------------|--|-------|-------|------|----------------|----------------|
| Select one of the following: | | | | | | |
| Q8B84B | HPE Nimble Storage 2x1GbE 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8B85B | HPE Nimble Storage 4x1GbE 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8B88B | HPE Nimble Storage 2x10GbE 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8B89B | HPE Nimble Storage 4x10GbE 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8B86B | HPE Nimble Storage 2x10GBASE-T 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8B87B | HPE Nimble Storage 4x10GBASE-T 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8B90B | HPE Nimble Storage 2x16Gb Fibre Channel 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8B91B | HPE Nimble Storage 4x16Gb Fibre Channel 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8B92B | HPE Nimble Storage 6x16Gb Fibre Channel 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8B95B | HPE Nimble Storage 2x10GbE 2-port and 2x16Gb Fibre Channel 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8B96B | HPE Nimble Storage 2x10GbE 2-port and 4x16Gb Fibre Channel 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8B93B | HPE Nimble Storage 2x10GBASE-T 2-port and 2x16Gb Fibre Channel 2-port FIO Adapter Kit2 | No | No | No | Yes | Yes |
| Q8B94B | HPE Nimble Storage 2x10GBASE-T 2-port and 4x16Gb Fibre Channel 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8B98B | HPE Nimble Storage 4x10GbE 2-port and 2x16Gb Fibre Channel 2-port FIO Adapter Kit | No | No | No | Yes | Yes |

Configuration Information

| | | | | | | |
|--------|---|-----|-----|-----|-----|-----|
| Q8B97B | HPE Nimble Storage 4x10GBASE-T 2-port and 2x16Gb Fibre Channel 2-port Adapter Kit | No | No | No | Yes | Yes |
| Q8B99B | HPE Nimble Storage 2x1GbE 2-port and 2x10GBASE-T 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C00B | HPE Nimble Storage 2x1GbE 2-port and 4x10GBASE-T 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C01B | HPE Nimble Storage 6x10GbE 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C02B | HPE Nimble Storage 6x10GBASE-T 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C03B | HPE Nimble Storage 2x16Gb Fibre Channel 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C04B | HPE Nimble Storage 4x16Gb Fibre Channel 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C05B | HPE Nimble Storage 6x16Gb Fibre Channel 4-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C17B | HPE Nimble Storage 2x10GbE 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C18B | HPE Nimble Storage 4x10GbE 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C19B | HPE Nimble Storage 6x10GbE 4-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C20B | HPE Nimble Storage 2x10GBASE-T 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C21B | HPE Nimble Storage 4x10GBASE-T 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C22B | HPE Nimble Storage 6x10GBASE-T 4-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C23B | HPE Nimble Storage 2x10GbE 4-port and 4x16Gb Fibre Channel 4-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C06B | HPE Nimble Storage 2x10GbE 2-port and 4x16Gb Fibre Channel 4-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C24B | HPE Nimble Storage 4x10GbE 4-port and 2x16Gb Fibre Channel 4-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C07B | HPE Nimble Storage 4x10GbE 2-port and 2x16Gb Fibre Channel 4-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C08B | HPE Nimble Storage 2x10GbE 2-port and 2x16Gb FC 4-port and 2x16Gb FC 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C09B | HPE Nimble Storage 2x1GbE 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C11B | HPE Nimble Storage 4x1GbE 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C12B | HPE Nimble Storage 6x1GbE 4-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C13B | HPE Nimble Storage 2x1GbE 4-port and 2x16Gb Fibre Channel 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C14B | HPE Nimble Storage 2x1GbE 4-port and 2x10GbE 2-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| Q8C15B | HPE Nimble Storage 2x1GbE 4-port and 4x16Gb Fibre Channel 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C16B | HPE Nimble Storage 2x1GbE 4-port and 4x10GbE 2-port FIO Adapter Kit | No | No | No | Yes | Yes |
| Q8C10B | HPE Nimble Storage 2x10GBASE-T 2-port and 4x16Gb Fibre Channel 4-port FIO Adapter Kit | No | No | No | Yes | Yes |
| R0N84A | HPE Nimble Storage 2x10GbE 2-port and 2x16Gb Fibre Channel 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |
| R0N85A | HPE Nimble Storage 2x10GBASE-T 2-port and 2x16Gb Fibre Channel 4-port FIO Adapter Kit | Yes | Yes | Yes | Yes | Yes |

Configuration Information

Step 5 – Add Expansion Shelves

ES3 Adaptive Expansion Shelves

Add up to six (6) ES3 Adaptive expansion shelves to each HF-Series array. Mix any options below up to array maximum capacity. Please refer to configuration guidelines for specific array capacity limits.

| Mix any of the following options up to platform max: | | HF20H | HF20C | HF20 | HF40/ HF40C | HF60/ HF60C |
|---|---|-------|-------|-------|------------------|------------------|
| SKU | SKU Description | | | | | |
| R0N82A | HPE Nimble Storage HF20C Adaptive ES3 126TB (21x6TB) HDD 3.8TB Cache CTO Expansion Shelf | No | Yes | No | Yes ¹ | Yes ¹ |
| R0N83A | HPE Nimble Storage HF20C Adaptive ES3 210TB (21x10TB) HDD 4.8TB Cache CTO Expansion Shelf | No | Yes | No | Yes ¹ | Yes ¹ |
| Q8B48B | HPE Nimble Storage HF20/20C/20H Adaptive ES3 21TB (21x1TB) HDD 1.44TB Cache CTO Expansion Shelf | Yes | Yes | Yes | No | No |
| Q8B49B | HPE Nimble Storage HF20/20C/20H Adaptive ES3 42TB (21x2TB) HDD 2.88TB Cache CTO Expansion Shelf | Yes | Yes | Yes | No | No |
| Q8B50B | HPE Nimble Storage HF20/20C/20H Adaptive ES3 84TB (21x4TB) HDD 5.76TB Cache CTO Expansion Shelf | Yes | Yes | Yes | No | No |
| Q8B51B | HPE Nimble Storage HF20/20H Adaptive ES3 126TB (21x6TB) HDD 9.6TB Cache CTO Expansion Shelf | Yes | | Yes | No | No |
| Q8H33A | HPE Nimble Storage HF40/60 Adaptive ES3 21TB (21x1TB) HDD 1.44TB Cache CTO Expansion Shelf | No | No | No | Yes | Yes |
| Q8H34A | HPE Nimble Storage HF40/60 Adaptive ES3 42TB (21x2TB) HDD 2.88TB Cache CTO Expansion Shelf | No | No | No | Yes | Yes |
| Q8H35A | HPE Nimble Storage HF40/60 Adaptive ES3 84TB (21x4TB) HDD 5.76TB Cache CTO Expansion Shelf | No | No | No | Yes | Yes |
| Q8G47B | HPE Nimble Storage HF40/60 Adaptive ES3 126TB (21x6TB) HDD 9.6TB Cache CTO Expansion Shelf | No | No | No | Yes ² | Yes ² |
| Q8G48B | HPE Nimble Storage HF40/60 Adaptive ES3 210TB (21x10TB) HDD 17.28TB Cache CTO Expansion Shelf | No | No | No | Yes ² | Yes ² |
| Platform Max SSD capacity (RAW)= (Head SSD + ES3 SSD) capacity (GB) | | 28TB | 38 TB | 28 TB | 48/ 60 TB | 156 TB |

¹ Not supported with HF40 and HF60

² Not supported with HF40C and HF60C

Optional Cache for ES3 Expansion Shelves

Only ONE of the following options can be selected per shelf.

Please refer to configuration guidelines for specific array cache capacity limits.

| ONE of the following SSD cache options can be selected: | | HF20H | HF20C | HF20 | HF40/ HF40C | HF60/ HF60C |
|---|--|-------|-------|------|----------------|----------------|
| Q8C25B | HPE Nimble Storage HF Adaptive ES3 Expansion Shelf 2.88TB (3x960GB) FIO Cache Bundle | Yes | Yes | Yes | Yes | Yes |
| Q8C26B | HPE Nimble Storage HF Adaptive ES3 Expansion Shelf 5.76TB (3x1.92TB) FIO Cache Bundle | Yes | Yes | Yes | Yes | Yes |
| Q8C28B | HPE Nimble Storage HF Adaptive ES3 Expansion Shelf 11.52TB (3x3.84TB) FIO Cache Bundle | Yes | Yes | Yes | Yes | Yes |
| Platform Max SSD capacity (RAW)= (Head SSD + ES3 SSD) capacity (GB) | | 28TB | 28TB | 28TB | 48/60TB | 156TB |

Configuration Information

Step 6 – Add Support (Mandatory)

Support recommendations are designed to help you enhance technology operations, lower risk and make it easier for you to seek the right balance between affordability and service-level commitments. Depending on your individual support needs, choose from three levels of care that cover the entire lifecycle to better address your needs from 1, 3, 4 and 5 year durations for service levels ranging from Next Business Day parts exchange to 4 hour onsite response.

| | |
|--|-----------------|
| NS 1/3/4/5Y FC NBD Parts Exchange Support | *HT7A1A1/3/4/5 |
| NS 1/3/4/5Y FC NBD Parts Exchange w DMR Support | HT7A2A1/3/4/5 |
| NS 1/3/4/5Y FC 4H Parts Exchange Support | HT6Z0A1/3/4/5 |
| NS 1/3/4/5Y FC 4H Parts Exchange w DMR Support | HT6Z1A1/3/4/5 |
| NS 1/3/4/5Y FC 4H Onsite Exchange Support | HT6Z2A1/3/4/5 |
| NS 1/3/4/5Y FC 4H Onsite Exchange w DMR Support | HT6Z3A1/3/4/5 |
| NS 1/3/4/5Y FC NBD Onsite Exchange Support | **HT6Z4A1/3/4/5 |
| NS 1/3/4/5Y FC NBD Onsite Exchange w DMR Support | **HT6Z5A1/3/4/5 |

NOTES:

* Minimum support required 1 year Next Business Day Parts Exchange.

** Support level available in Japan only.

Controller Refresh

The Controller Refresh program provides customers with a new controller after three years provided they meet the terms of the Controller Refresh program. To add Controller Refresh it needs to be configured with the initial Nimble array order. For more details on the Controller Refresh program, please see the [timeless storage](#) brochure.

| | |
|--|-------------|
| HPE NS 3Y/5Y FC NBD PExch L1 Controller Refresh Support | HT7G8A3/5 |
| HPE NS 3Y/5Y FC NBD PExch DMR L1 Controller Refresh Support | HT7G9A3/5 |
| HPE NS 3Y/5Y FC NBD PExch L2 Controller Refresh Support | HT7H6A3/5 |
| HPE NS 3Y/5Y FC NBD PExch DMR L2 Controller Refresh Support | HT7H7A3/5 |
| HPE NS 3Y/5Y FC NBD PExch L3 Controller Refresh Support | HT7J4A3/5 |
| HPE NS 3Y/5Y FC NBD PExch DMR L3 Controller Refresh Support | HT7J5A3/5 |
| HPE NS 3Y/5Y FC NBD Onsite L1 Controller Refresh Support | **HT7H4A3/5 |
| HPE NS 3Y/5Y FC NBD Onsite DMR L1 Controller Refresh Support | **HT7H5A3/5 |
| HPE NS 3Y/5Y FC NBD Onsite L2 Controller Refresh Support | **HT7J2A3/5 |
| HPE NS 3Y/5Y FC NBD Onsite DMRL2 Controller Refresh Support | **HT7J3A3/5 |
| HPE NS 3Y/5Y FC NBD Onsite L3 Controller Refresh Support | **HT7K0A3/5 |
| HPE NS 3Y/5Y FC NBD Onsite DMR L3 Controller Refresh Support | **HT7K1A3/5 |
| HPE NS 3Y/5Y FC 4H PExch L1 Controller Refresh Support | HT7H0A3/5 |
| HPE NS 3Y/5Y FC 4H PExch DMR L1 Controller Refresh Support | HT7H1A3/5 |
| HPE NS 3Y/5Y FC 4H PExch L2 Controller Refresh Support | HT7H8A3/5 |
| HPE NS 3Y/5Y FC 4H PExch DMR L2 Controller Refresh Support | HT7H9A3/5 |
| HPE NS 3Y/5Y FC 4H PExch L3 Controller Refresh Support | HT7J6A3/5 |
| HPE NS 3Y/5Y FC 4H PExch DMR L3 Controller Refresh Support | HT7J7A3/5 |
| HPE NS 3Y/5Y FC 4H Onsite L1 Controller Refresh Support | HT7H2A3/5 |
| HPE NS 3Y/5Y FC 4H Onsite DMR L1 Controller Refresh Support | HT7H3A3/5 |

Configuration Information

| | |
|---|-----------|
| HPE NS 3Y/5Y FC 4H Onsite L2 Controller Refresh Support | HT7J0A3/5 |
| HPE NS 3Y/5Y FC 4H Onsite DMR L2 Controller Refresh Support | HT7J1A3/5 |
| HPE NS 3Y/5Y FC 4H Onsite L3 Controller Refresh Support | HT7J8A3/5 |
| HPE NS 3Y/5Y FC 4H Onsite DMR L3 Controller Refresh Support | HT7J9A3/5 |

*Controller Refresh is available as 3-year or 5-year support offerings

** Support level available in Japan only.

Installation Services

Installation Services are intended to guide you from start to finish and to help make your installation a success. Our engagement includes the following phases:

Array Installation

- Inventory and verify HPE Nimble Storage equipment against the sales order
- Physically rack and cable all HPE Nimble Storage equipment, including connecting network cables provided by the customer
- Conduct power-on tests and verify operation
- Add the array to an existing HPE Nimble Storage group, if applicable
- Configure array's basic management, monitoring, & reporting capabilities
- Configure array for additional data networks / SAN connectivity as needed
- Upgrade the array to the latest recommended HPE Nimble OS version

NOTE: Installation services are optional.

| | |
|---|-------------|
| HPE Nimble Storage Array Start-up service | HA114A1#5MR |
| HPE Nimble Storage Array Upgrade service | HA124A1#5MS |

Racks

HPE Nimble Storage arrays and expansion shelves are compatible with industry standard 4-post EIA 19 inch racks with square mounting holes, including HPE 36U, 42U and 48U Enterprise Shock Racks. HPE recommends HPE racks with a depth of 1200mm to best accommodate the length of the Nimble Storage chassis; the HPE 1200mm rack provides ample room for cabling and ease of serviceability. HPE racks with a depth of 1075mm can be used but may have limited space for cabling and component access. If a 3rd party rack with a depth less than 1075mm is used, the rear doors cannot be fully closed.

Recommended Racks:

HPE G2 Enterprise Series Racks

- HPE 48U 600mmx1200mm G2 Enterprise Rack
- HPE 48U 800mmx1200mm G2 Enterprise Rack
- HPE 42U 600mmx1200mm G2 Enterprise Rack
- HPE 42U 800mmx1200mm G2 Enterprise Rack

HPE G2 Advanced Series Racks

- HPE 48U 600mmx1200mm G2 Advanced Rack
- HPE 48U 800mmx1200mm G2 Advanced Rack
- HPE 42U 600mmx1200mm G2 Advanced Rack
- HPE 42U 800mmx1200mm G2 Advanced Rack
- HPE 36U 600mmx1200mm G2 Advanced Rack
- HPE 36U 800mmx1200mm G2 Advanced Rack

For more information on the HPE rack offerings, please see the following URL: <https://www.hpe.com/info/rackandpower>

For more information on rack options, see: <http://www.hpe.com/products/rackoptions>

For more information on PDUs, see: <http://www.hpe.com/servers/pdu>

Configuration Information

Required and additional power cords

HPE Nimble Storage Arrays and expansion shelves do not ship with any power cords by default and require a minimum of two power cords per system. Please ensure these are selected at time of quoting. A pair of power cords are required when connecting base arrays (C19/C14 or C19/C20) or expansion shelves (C13/C14) to Rack-Mounted Power Distribution Units (PDU). A pair of country/region specific power cords are required when connecting base arrays or expansion shelves to standard office wall power outlets.

| | |
|---|--------|
| HPE Nimble Storage NEMA 5-15P to C19 125V 15Amp 2.5m US FIO Power Cord | R0P83A |
| HPE Nimble Storage IEC 60320 C14 to C19 250V 15Amp 1.8m FIO Power Cord | R0P84A |
| HPE Nimble Storage AS3112 to C19 250V 16Amp 1.8m AU FIO Power Cord | Q8J02A |
| HPE Nimble Storage Schuko to C19 250V 16Amp 1.8m EU FIO Power Cord | Q8J03A |
| HPE Nimble Storage BS 1363 UK10 to C19 250V 16Amp 1.8m UK FIO Power Cord | Q8J04A |
| HPE Nimble Storage NEMA L5-20P to C19 125V 20Amp 2.5m US FIO Power Cord | Q8J05A |
| HPE Nimble Storage GB2099 to C19 250V 16Amp 1.8m CN FIO Power Cord | Q8J06A |
| HPE Nimble Storage KSC8305 to C19 250V 16Amp 1.8m KR FIO Power Cord | Q8J07A |
| HPE Nimble Storage JIS8303 to C19 125V 15Amp 1.8m TW/JP FIO Power Cord | Q8J08A |
| HPE Nimble Storage JIS8303 6-30 to C19 250V 15Amp 1.8m JP FIO Power Cord | Q8J09A |
| HPE Nimble Storage IS1293 to LS-60 250V 16Amp 1.8m IN FIO Power Cord | Q8J10A |
| HPE Nimble Storage SAN164-1 to C19 250V 16Amp 1.8m ZA FIO Power Cord | Q8J11A |
| HPE Nimble Storage SI32 to C19 250V 16Amp 1.8m IL FIO Power Cord | Q8J12A |
| HPE Nimble Storage CEI 23-16 to C19 250V 16Amp 1.8m IT FIO Power Cord | Q8J13A |
| HPE Nimble Storage C19 to C20 250V 16Amp 1.8m PDU Base Array FIO Power Cord | Q8J14A |
| HPE Nimble Storage AS 3112 to C13 250V 10Amp 1.8m AU FIO Power Cord | Q8J15A |
| HPE Nimble Storage Schuko to C13 250V 10Amp 1.8m EU FIO Power Cord | Q8J16A |
| HPE Nimble Storage BS1363 UK10 to C13 250V 10Amp 1.8m UK FIO Power Cord | Q8J17A |
| HPE Nimble Storage NEMA 5-15P to C13 125V 10Amp 1.8m US FIO Power Cord | Q8J18A |
| HPE Nimble Storage GB2099 to C13 250V 10Amp 1.8m CN FIO Power Cord | Q8J19A |
| HPE Nimble Storage KSC8305 to C13 250V 10Amp 1.8m KR FIO Power Cord | Q8J20A |
| HPE Nimble Storage JIS8303 to C13 125V 12Amp 1.8m TW/JP FIO Power Cord | Q8J21A |
| HPE Nimble Storage JIS8303 to C13 250V 15Amp 1.8m JP FIO Power Cord | Q8J22A |
| HPE Nimble Storage IS1293 to C13 250V 10Amp 1.8m IN FIO Power Cord | Q8J23A |
| HPE Nimble Storage SANS164-1 to C13 250V 10Amp 1.8m ZA FIO Power Cord | Q8J24A |
| HPE Nimble Storage SI32 to C13 250V 10Amp 1.8m IL FIO Power Cord | Q8J25A |
| HPE Nimble Storage CEI23-16 to C13 250V 10Amp 1.8m IT FIO Power Cord | Q8J26A |
| HPE Nimble Storage C13 to C14 250V 10Amp 1.8m Universal FIO Power Cord | Q8J27A |

Field Upgrade Options

The following product options are to upgrade currently installed Adaptive Flash Arrays

Configuration Information

| Controller Upgrades | | | | | | |
|----------------------|---|-------|-------|------|------------|------------|
| SKU | SKU Description | HF20H | HF20C | HF20 | HF40/HF40C | HF60/HF60C |
| Q8H51A | HPE Nimble Storage HF20X to HF40 Adaptive Array Dual Controller Field Upgrade | Yes | Yes | Yes | No | No |
| Q8H52A | HPE Nimble Storage HF20/40 to HF60 Adaptive Array Dual Controller Field Upgrade | No | Yes | Yes | Yes | No |
| HDD Capacity Upgrade | | | | | | |
| SKU | SKU Description | HF20H | HF20C | HF20 | HF40/HF40C | HF60/HF60C |
| Max one (1) | | | | | | |
| Q8D07B | HPE Nimble Storage HF20H Adaptive Array 11TB (11x1TB) HDD Field Upgrade | Yes | No | No | No | No |

| Cache Upgrades | | | | | | |
|---|---|-------|-------|------|------------|------------|
| Only one of the following options can be selected | | HF20H | HF20C | HF20 | HF40/HF40C | HF60/HF60C |
| Q8D11B | HPE Nimble Storage HF20H Adaptive Array 480GB (2x240GB) Cache Field Upgrade | Yes | No | No | No | No |
| Q8D12B | HPE Nimble Storage HF20H Adaptive Array 960GB (2x480GB) Cache Field Upgrade | Yes | No | No | No | No |
| Q8D13B | HPE Nimble Storage HF20/20C Adaptive Array 720GB (3x240GB) Cache Field Upgrade | No | Yes | Yes | No | No |
| Q8D14B | HPE Nimble Storage HF20/20C Adaptive Array 1.44TB (3x480GB) Cache Field Upgrade | No | Yes | Yes | No | No |
| Q8H85A | HPE Nimble Storage HF20/20C Adaptive Array 2.88TB (3x960GB) Cache Field Upgrade | No | Yes | Yes | No | No |
| Q8H86A | HPE Nimble Storage HF20/20C Adaptive Array 5.76TB (3x1.92TB) Cache Field Upgrade | No | Yes | Yes | No | No |
| Q8H87A | HPE Nimble Storage HF20/20C Adaptive Array 11.52TB (3x3.84TB) Cache Field Upgrade | No | Yes | Yes | No | No |
| Q8H58A | HPE Nimble Storage HF40/60 Adaptive Array 720GB (3x240GB) Cache Field Upgrade | No | Yes | Yes | No | No |
| Q8H59A | HPE Nimble Storage HF40/60 Adaptive Array 1.44TB (3x480GB) Cache Field Upgrade | No | No | No | Yes | Yes |
| Q8C99B | HPE Nimble Storage HF40/60 Adaptive Array 2.88TB (3x960GB) Cache Field Upgrade | No | No | No | Yes | Yes |
| Q8D00B | HPE Nimble Storage HF40/60 Adaptive Array 5.76TB (3x1.92TB) Cache Field Upgrade | No | No | No | Yes | Yes |
| Q8D01B | HPE Nimble Storage HF40/60 Adaptive Array 11.52TB (3x3.84TB) Cache Field Upgrade | No | No | No | Yes | Yes |

Configuration Information

| Networking Upgrades | | | | | | |
|---------------------|--|-------|-------|------|------------|------------|
| SKU | | HF20H | HF20C | HF20 | HF40/HF40C | HF60/HF60C |
| Q8C64B | HPE Nimble Storage 2x1GbE 2-port Adapter Field Upgrade | Yes | Yes | Yes | Yes | Yes |
| Q8C63B | HPE Nimble Storage 2x10GbE 2-port Adapter Field Upgrade | Yes | Yes | Yes | Yes | Yes |
| Q8C62B | HPE Nimble Storage 2x10GBASE-T 2-port Adapter Field Upgrade | Yes | Yes | Yes | Yes | Yes |
| Q8C65B | HPE Nimble Storage 2x16Gb Fibre Channel 2-port Adapter Field Upgrade | Yes | Yes | Yes | Yes | Yes |
| Q8C66B | HPE Nimble Storage 2x16Gb Fibre Channel 4-port Adapter Field Upgrade | Yes | Yes | Yes | Yes | Yes |
| Q8C68B | HPE Nimble Storage 2x10GbE 4-port Adapter Field Upgrade | Yes | Yes | Yes | Yes | Yes |
| Q8C69B | HPE Nimble Storage 2x10GBASE-T 4-port Adapter Field Upgrade | Yes | Yes | Yes | Yes | Yes |
| Q8C67B | HPE Nimble Storage 2x1GbE 4-port Adapter Field Upgrade | Yes | Yes | Yes | Yes | Yes |

| Upgrade Existing ES3 Shelf | | | | | | |
|----------------------------|---|-------|-------|------|------------|------------|
| SKU | | HF20H | HF20C | HF20 | HF40/HF40C | HF60/HF60C |
| Q8C48B | HPE Nimble Storage HF Adaptive ES3 2.88TB (3x960GB) Cache Field Upgrade | Yes | Yes | Yes | Yes | Yes |
| Q8C49B | HPE Nimble Storage HF Hybrid ES3 5.76TB (3x1.92TB) Cache Field Upgrade | Yes | Yes | Yes | Yes | Yes |
| Q8C50B | HPE Nimble Storage HF Adaptive ES3 11.52TB (3x3.84TB) Cache Field Upgrade | Yes | Yes | Yes | Yes | Yes |

| DC Power Supply unit (PSU) | | | | | | |
|----------------------------|-------|------|------------|------------|---|--------|
| HF20H | HF20C | HF20 | HF40/HF40C | HF60/HF60C | | |
| Yes | Yes | Yes | Yes | Yes | HPE Nimble Storage AF/HF 3000W Dual DC Power Supply Kit | ROR06A |

NOTE: The DC PSU kit includes two (2) DC PSUs; one (1) DC PSU kit per array or shelf should be ordered for systems to be installed in environments utilizing DC power infrastructure

NOTE: If NEBS compliance is required, the DC PSU kit should only be ordered with new arrays (which include DC grounding posts)

Technical Specifications

| Physical Dimensions | HPE Nimble Storage HF20/20H/20C/40/60/80 | HPE Nimble Storage ES3 Expansion Shelf |
|---------------------|---|---|
| Width in/mm | 17.3/439 | 17.3/439 |
| Depth in/mm | 35/890 | 35/890 |
| Height in/mm/U | 6.92/175.8/4 | 6.92/175.8/4 |
| Weight lb/kg | 135/65 | 115/52 |

| Power Requirements | HF20/ HF20C | HF20H | HF40/ HF40C | HF60/ HF60C | ES3 |
|--|--|-----------------------|--------------------|-----------------------|----------------------|
| Input Voltage, frequency (1200W AC PSU w/C14 connector) | 100-120V, 50-60Hz 200-240V, 50-60Hz | | | N/A | 100-120V 200-240V |
| Input Voltage, frequency (3000W AC PSU w/C20 connector) | 100-120V, 50-60Hz 200-240V, 50-60Hz | | | | N/A |
| Input Voltage (3000W DC PSU) | -48/-72 VDC, 40A | | | | |
| Max power requirements (Watts/kVA) | 750 W / 0.833 kVA | 650 W 0.722 kVA | 850 W 0.944 kVA | 900 W 1.000 kVA | 350 W 0.389 kVA |
| Thermal (BTU) | 2460 BTU | 2132 BTU | 2788 BTU | 2952 BTU | 1147 BTU |

Environmental Specifications⁴

| | |
|---------------------------------------|--|
| Operating Temperature | 10 - 35° C (50 - 95° F) Reduce rating by 1° F for each 1000 ft altitude (1.8° C/1,000 m) |
| Shipping Temperature | 0° C - 40° C (32° F - 104° F) Maximum rate of change is 20°C/hr (36°F/hr) |
| Operating Altitude (ft/m) max. | 10,000 ft / 3,048 m |
| Shipping Altitude (ft/m) max. | 40,000ft/ 12,192 m |
| Humidity | 8 - 90%, non-condensing |
| Shipping Humidity | 5 - 95%, non-condensing |
| Operating Vibration | 0.25 G, Sine 5 - 200 Hz (approx. 15 min/axis); 0.4 GRMS, Random 5 - 200 Hz (approx. 60 min/axis) |
| Non-operating Vibration | 0.5 G, Sine 5 - 200 Hz (approx. 15 min/axis); 0.98 GRMS, Random 5 - 500Hz (approximate 30 min/axis) |
| Operating Shock | 20 G, 2.5ms, half-sine, one shock on each side |
| Non-operating Shock | 20 G, 10ms, square wave, one shock on each side |

Electromagnetic Compatibility

- Subpart B of Part 15 of FCC Rules for Class A digital devices
- ICES-003, Issue 6, dated January 2016 (Class A)
- VCCI V-3: April 2014 (Class A)
- EN 55022:2010
- CISPR 22:2008
- AS/NZS CISPR 22:2009 +A1:2010
- EN55032:2012
- CISPR 32:2012
- EN 55024:2010
- CISPR 24:2010 +A1:2015
- TCVN 7189:2009
- NBTC TS 3001-2555
- TP TC 020/2011

Technical Specifications

Safety

- EN60950-1:2005 (Second Edition); Am1:2009 + Am2:2013
- IEC 60950-1:2005 (Second Edition); Am1:2009 + Am2:2013
- EN60950-1:2006/A11:2009/A1:2010/A12:2011/A2:2013
- UL/IEC 60960-1 2nd Ed. Am1 + Am2
- CNS14336-1 ('99)
- CNS13438 ('95)
- NOM-019-SCFI-1998
- NBTC TS 4001-2550
- TP TC 004/2011
- IS 13252 (PART 1):2010 +A1:2013 + A2:2-15
- SANS IEC 60950-1

NOTE: ⁴ Specifications are subject to change without notice.

Certifications / Markings

- | | |
|-----------------|---------------------------------|
| • UL | • NOM |
| • cUL | • MoEc |
| • CE | • NBTC SDoC |
| • FCC Class A | • CITC/CoC |
| • IC Class A | • EAC |
| • VCCI Class A | • BIS |
| • RCM | • LOA (S. Africa) |
| • BSMI Class A | • RoHS 2011/65/EU, EN50581:2012 |
| • KC | • WEEE |
| • CCC Exemption | |
-

Summary of Changes

| Date | Version History | Action | Description of Change |
|-------------|-----------------|---------|--|
| 03-Feb-2020 | Version 22 | Changed | Q8B95B SKU description was updated. |
| 04-Nov-2019 | Version 21 | Changed | Technical Specifications section was updated. |
| 07-Oct-2019 | Version 20 | Changed | Configuration Information section was updated. |
| 05-Aug-2019 | Version 19 | Changed | Overview and Configuration Information sections were updated. |
| 01-Jul-2019 | Version 18 | Changed | Overview, Configuration Information and Technical Specifications sections were updated. |
| 03-Jun-2019 | Version 17 | Changed | Overview and Technical Specifications sections were updated. |
| 02-Apr-2019 | Version 16 | Changed | Configuration Information section was updated. |
| 04-Mar-2019 | Version 15 | Changed | Configuration Information section was updated. |
| 04-Feb-2019 | Version 14 | Changed | Overview and Configuration Information sections were updated. |
| 07-Jan-2019 | Version 13 | Changed | Overview and Configuration Information sections were updated |
| 03-Dec-2018 | Version 12 | Added | Added HF40C Array and HF60C Array |
| | | Changed | Overview and Configuration Information sections were updated. |
| 05-Nov-2018 | Version 11 | Changed | Description of Change Overview, Service and Support and Configuration Information sections were revised |
| 01-Oct-2018 | Version 10 | Changed | Overview and Configuration Information sections were updated |
| 13-Aug-2018 | Version 9 | Changed | Configuration Information section was revised |
| 06-Aug-2018 | Version 8 | Added | New upgrade options were added. |
| | | Changed | Configuration Information section was updated. |
| 04-Jun-2018 | Version 7 | Changed | HPE Nimble Storage Adaptive Flash Array models and Configuration Information were revised. |
| 14-May-2018 | Version 6 | Changed | Overview section was revised. |
| 07-May-2018 | Version 5 | Changed | Overview, Configuration Information, and Technical Specifications were revised. |
| 13-Nov-2017 | Version 4 | Changed | Overview and Configuration Information were revised. |
| 06-Nov-2017 | Version 3 | Changed | Added information on the entire HPE Nimble Storage CS-Series portfolio. |
| 12-Jun-2017 | Version 2 | Changed | Detail on included power cords and SAS cables. |
| 05-Jun-2017 | Version 1 | Created | Created first version, including CS1000 and CS1000H. |



Sign up for updates



© Copyright 2020 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

a00008274enw - 15933 - Worldwide - V22 - 03-February-2020